

CP-**UA-DL04-35**

Bluetooth Smart Lock

- 4-way opening: Bluetooth, Mifare Cards, passwords and mechanical keys
- Privacy password: xxx+ password+ xxx, preventing password to be seen by others
- Passage Mode and Non-disturbance Mode optional
- Auto lock when come across a consecutive invalid passwords or cards
- Low Voltage alarm(<4.5V)
- Huge storage: 50 cards, 50 passwords, 8 Bluetooth
- Emergency power supply outside
- Two colors optional
- Zinc alloy material



About CP PLUS

The brand that is on its way to lead the world when it comes to the security and surveillance industry, CP PLUS, keeps bombarding the market with the most reliable range of products that have been designed carefully and methodically to automate the whole surveillance and security process, no matter how big your premises are.

It was the initiative to help the public in the area where they are the most vulnerable and to empower the sense of safety in our hearts that had conceptualized CP PLUS. And embarking on its mission to make the world a safer and more secure place has taken the brand's journey to unprecedented levels even when compared to international competitors.



CP-UA-DL04-35

Bluetooth Smart Lock

| Feature | Specification |
|---------------------------|---|
| Card Type | Mifare 1 |
| Card Features | Contactless, high security, all-in-one possible |
| Sensor Distance | < 20mm |
| Sensor Time | < 0.5s |
| Storage Capacity Card | 50 |
| Keyboard Type | All-touch keyboard |
| Password Length | 6-12 bits |
| Password Storage Capacity | 50 |
| Door Thickness | 35-65mm (customizable) |
| Backset | 60/70mm |
| Material | Zinc alloy |
| Working Voltage | 6V, AA alkaline battery (4pcs) |
| Battery Life | About 1 year (10 units/D) |
| Low Battery Warning | < DC4.5V |
| Emergency Power Supply | 9V battery |
| Working Temperature | -20°C~+55°C |
| Relative Humidity | 10%~93% |
| Salt spray test | ≥200h |
| Lock case test | ≥100000 times |
| Package size | 315x230x160(mm) |
| Gross weight | 3.3Kg |
| Restore Default | Support |
| Reset | Support |
| Built-in Buzzer | Support |